

SPECIFICATION



- Features :• Universal AC input / Full range
- · AC input active surge current limiting
- Built-in 5V/0.3A,12V/0.8Aauxiliary power
- . Built-in active PFC function, PF>0.98
- Protections: Short circuit / Overload / Over voltage / Over temperature
- Output voltage can be trimmed between 20 ~ 110% of the rated output voltage
- · Forced air cooling by built-in DC fan
- High power density 21.4w/inch³
- 1U low profile 41mm
- · Active current sharing
- DC OK Signal
- · Built-in remote ON-OFF control
- · Built-in remote sense function

· 3 years warranty



MODEL	ATION	RSP-2000-12	RSP-2000-24	RSP-2000-48
	DC VOLTAGE	12V	24V	48V
ОИТРИТ	RATED CURRENT	100A	80A	42A
	CURRENT RANGE	0 ~ 100A	0~80A	0 ~ 42A
	RATED POWER	1200W	1920W	2016W
	RIPPLE & NOISE (max.) Note.2	**	200mVp-p	300mVp-p
	VOLTAGE ADJ. RANGE	10.5 ~ 14V	21 ~ 28V	42 ~ 56V
	VOLTAGE TOLERANCE Note.3		±1.0%	±1.0%
	LINE REGULATION	±0.5%	±0.5%	±0.5%
	LOAD REGULATION	±0.5%	±0.5%	±0.5%
		1500ms, 60ms at full load	10.3%	_0.5 %
	SETUP, RISE TIME			
	HOLD UP TIME (Typ.)	16ms/230VAC at 75% load 10ms/230VAC at full load		
INPUT		90 ~ 264VAC 127 ~ 370VDC		
	FREQUENCY RANGE	47 ~ 63Hz		
	POWER FACTOR (Typ.)	0.98/230VAC at full load	00.5%	000/
	EFFICIENCY (Typ.)	86%	90.5%	92%
	AC CURRENT (Typ.)	13A/115VAC 7A/230VAC 16A/115VAC 11A/230VAC		
	INRUSH CURRENT (Typ.)	25A/115VAC 50A/230VAC		
	LEAKAGE CURRENT	<2.0mA / 240VAC		
PROTECTION	OVERLOAD	105 ~ 125% rated output power		
		71	covers automatically after fault condition is rer	noved
	OVER VOLTAGE	14.7 ~ 17.5V	29.5 ~ 35V	57.6 ~ 67.2V
		Protection type: Shut down o/p voltage, re-power on to recover		
	OVER TEMPERATURE	85°C±5°C (TSW2) detect on heatsink of O/P diode; 75°C±5°C (TSW1) detect on heatsink of power transistor		
		Protection type : Shut down o/p voltage, recovers automatically after temperature goes down		
FUNCTION	AUXILIARY POWER(AUX)	5V @ 0.3A / 12V @ 0.8A		
	REMOTE ON/OFF CONTROL Note.6	Power on: short between on/off(pin6) & -S(pin2) Power off: open between on/off(pin6) & -S(pin2)		
	DC OK SIGNAL	The TTL signal out, PSU turn on = 3.3 ~ 5.6V; PSU turn off = 0 ~ 1V		
	OUTPUT VOLTAGE TRIM Note.6	Adjustment of output voltage is possible between 20 ~ 110% of rated output		
	CURRENT SHARING(CS)Note.7	Please refer to function manual		
ENVIRONMENT	WORKING TEMP.	-25 ~ +70°C (Refer to output load derating curve)		
	WORKING HUMIDITY	20 ~ 90% RH non-condensing		
	STORAGE TEMP., HUMIDITY	<mark>-40~+85℃, 10~</mark> 95% RH		
	TEMP. COEFFICIENT	±0.02%/°C (0~50°C)		
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes		
SAFETY & EMC (Note 4)	SAFETY STANDARDS	UL60950-1, TUV EN60950-1 approved		
	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC		
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms/500VDC		
	EMI CONDUCTION & RADIATION	Compliance to EN55022 (CISPR22)		
	HARMONIC CURRENT	Compliance to EN61000-3-2,-3		
	EMS IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11; ENV50204, EN55024, EN61000-6-2, EN61204-3, heavy industry level, criteria A		
	MTBF	K hrs min. MIL-HDBK-217F (25°C)	, , , , , , , , , , , , , , , , , , , ,	, , , , , , , , , , , , , , , , , , , ,
OTHERS	DIMENSION	295*127*41mm (L*W*H)		
	PACKING	Kg		
NOTE			put, rated load and 25°C of ambient tempe	iratura

NOTE

- All parameters NOT specially mentioned are measured at 230VAC input, rated load and 25 $^{\circ}$ C of ambient temperature.
- 2. Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.
- 3. Tolerance: includes set up tolerance, line regulation and load regulation.
- 4. The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets EMC directives.
- 5. Derating may be needed under low input voltages. Please check the derating curve for more details.
- 6. The power supply unit will have no output if the shorting connector is not assembled. It contains two shorting wires: one is from on/off(pin6) to -s(pin2) and the other is from Vco(pin8) to Vca(pin10). Please refter to function manual for details.
- 7. In parallel connection, maybe only one unit operate if the total output load is less than 5% of rated load condition.



